



# PK Kiln Specification Sheet

Model	Volts	Amps	Watts	Max. Cone	Copper Wire Size*	Fuse or Breaker Size
KM-1231PK	240	72	17300	10	2	90
KM-1231PK	208	80	16640	10	2	100
KM-1231PK-3ph	240	44.5	17300	10	6	60
KM-1231PK-3ph	208	51.5	17300	10	6	60
KM-1227PK	240	60	14300	10	4	80
KM-1227PK	208	69	14300	10	2	90
KM-1227PK-3ph	240	40	14300	10	6	50
KM-1227PK-3ph	208	46.7	14300	10	6	60

*\*An electrician will need to make the electrical connection. The kilns are "hard wired" to allow for greater amperage. For each additional 50 feet use heavier wire, numerically two numbers lower—for example, instead of #6, use #4. If you anticipate installing any larger kiln in the future, use the heavier wire.*